
thermoscientific



Version 1

XX21549-EN 0816S Revision A • August 2016



SMART Digest ImmunoAffinity (IA) Kits


Delivering Fast, Simple and Highly Reproducible Immunocapture and Digestion of Proteins

The Thermo Scientific™ SMART Digest™ ImmunoAffinity (IA) Kits are designed for biomarker quantitation. These proteins are often present at low levels in complex biological matrices. Immunoaffinity capture is typically employed to purify the sample and increase sensitivity. This step is often followed by protein digestion.

The SMART Digest IA kit is designed to remove the issues often associated with sample preparation of proteins by delivering a process which is:

- Fast
- Simple
- Highly reproducible
- Sensitive
- Compatible with automation


The SMART Digest IA kit achieves this by its unique design where the immunoaffinity reagents (either streptavidin, protein A or protein G) and heat activated thermally stable trypsin are co-immobilized onto a single bead.






Following the binding of a capture reagent to the bead, and enrichment of the target, the enzyme is activated at elevated temperatures for accelerated digestion under protein denaturing conditions. The resulting workflow is faster and easier than the traditional process. Magnetic and non-magnetic versions of the beads are available.


SMART Digest IA workflow compared to a traditional protein sample preparation workflow



Total time

15-24 hours





3-4 hours

How to use the SMART Digest IA Kit



Preparation of biotinylation solution

- Weigh out 5 mg of N-hydroxysuccinimide (NHS)-Biotin in a 1.5 mL tube.
- Add 1 mL dimethylsulfoxide (DMSO) to make a solution of 5 mg/mL NHS-Biotin in DMSO

Biotinylation of antibody or capture moiety

- As needed, dilute the stock solution of your antibody, or capture moiety to a working concentration by addition of PBS or other amine free buffer.
- To the working solution add 5 µL of 5 mg/mL biotinylation solution for each milligram of antibody or capture moiety in your working solution and mix thoroughly. For biotinylation of proteins at varying concentrations, see the table below.
- Allow the solution to react with continuous mixing at 1400 RPM, for at least 2 hours.
- Once the capture moiety is biotinylated, ≤5 µg of the biotinylated materials may be bound to every 30 µL of the beads.
- Add the biotinylated materials to the beads and allow them to react with continuous mixing at 1400 RPM, for at least 30 minutes.
- For bulk modifications, the beads should be reduced to their original volume following the binding of the capture moiety to the beads to allow for optimal dispensation (see page 7).

		NHS-Biotin guide for protein biotinylation Recommended Volume of 5 mg/mL NHS-Biotin (μL)						
	Protein Molarity μΜ (μmol/L)							
		0.1	1	5	10	25	100	
Sample Volume (mL)	1	0.08	0.82	4.1	8.19	20.48	81.94	
	0.5	0.04	0.41	2.05	4.1	10.24	40.97	
	0.25	0.02	0.2	1.02	2.05	5.12	20.48	
8	0.1	0.01	0.08	0.41	0.82	2.05	8.19	

Note: The optimum amount of biotin per protein is detailed in the table above. Too much biotin will leave remaining free biotin to outcompete for streptavidin binding sites on the SMART Digest IA resin. However, too little will result in insufficient biotinylation of the antibody, or protein for capture. This titering eliminates the need to dialyze, or otherwise remove any unreacted biotin from the antibody.

Cross-linking Procedure SMART Digest IA Kit, Protein A and G

Preparation of glutaraldehyde solution

• Make a solution of 0.01% glutaraldehyde in DMSO.


Antibody capture

- Incubate 5 μg of your antibody with 30 μL SMART Digest IA Protein A or G resin for 30 minutes at room temperature and 1400 RPM. For bulk modifications, scale the protocol as needed.
- Wash the resin with PBS* 3 times: centrifuge the resin, decant the majority of the supernatant, and then re-suspend the resin in fresh buffer. After the final wash, leave 45 µL of solution for every 30 µL of original slurry.

*The washing step may be performed with a buffer other than PBS, as long as it is amine free.

Cross-linking

- For every 45 μL of solution, add 5 μL of the 0.01% glutaraldehyde solution and incubate for 2.5 hours at room temperature and 1400 RPM.
- For every 50 μL of solution add 10 μL of 500mM TBS to quench any remaining glutaraldehyde. Incubate at room temperature and 1400 RPM for at least 10 minutes.
- When performing bulk modifications, the beads should be reduced to their original volume following the quenching step to allow for optimal dispensation (see page 7). For every 60 µL of solution present following the quenching step, 30 µL of supernatant should be decanted.



Preparation of Beads: Component 1

SMART Digest IA Kit, Streptavidin

- With the SMART Digest IA Streptavidin kit, biotinylated capture reagents may be added directly to the beads prior to sample addition.
- For every 30 μL of beads, add ≤5 μg biotinylated antibody or capture moiety.
- When performing bulk modifications, the beads should be reduced to their original volume following the binding of the capture moiety to the beads to allow for optimal dispensation (see page 7).

SMART Digest IA Kit, Protein A and G


- With the SMART Digest IA Protein A and G kits capture antibodies may be added directly to the beads then cross-linked into place as part of a targeted workflow.
- For every 30 µL of beads, add ≤5 µg of antibody.
- When performing bulk modifications, the beads should be reduced to their original volume following the binding of the capture moiety to the beads to allow for optimal dispensation (see page 7).
- Alternatively, samples can be added directly to the SMART Digest IA Protein A and G beads for bulk fractionation of immunoglobulins. For this workflow, no cross-linking is required.

Preparation of the Wash Buffer: Component 2

- Dissolve the contents of the Wash Buffer packet into 500 mL of deionized water.
- Add 100 mg NaN₃ (sodium azide) as a preservative and biocide. Once prepared, when not in use, the SMART Digest IA Wash Buffer solution should be stored at 4 °C.

Note: Sample dilution is not required for many workflows. If your workflow requires dilution, the wash buffer may be used as sample diluent.

Protein Capture Procedure



Protein Wash Procedure

Following the protein capture procedure, the beads need to be separated from the solution.



Non-magnetic option




- Centrifuge sample well/tube (1 min, 1300 RPM).
- Following centrifugation uncap the well/tube and reduce the sample volume to 50 μL or ¾ sample volume, whichever is less, with a pipette or similar device and discard the supernatant.

Magnetic option



- Place magnet to side of well/tube.
 The beads will be held in place.
- Following magnetization, uncap well/tube and aspirate all supernatant and discard.



- Add the wash buffer (component 2) to well/tube.
- Final sample volume is 400 μL.

Vortex thoroughly and wash beads.



Non-magnetic option



- Centrifuge sample well/tube (1 min, 1300 RPM).
- Remove 350 µL of supernatant.
- Replace with a fresh 350 µL of wash buffer.
- Perform these steps at least 4 times.

Magnetic option




- Place magnet to side of well/tube. The beads will be held in place.
- Remove the entire 400 µL volume of sample.
- Replace with 400 µL of wash buffer.
- Perform these steps at least 4 times.

Separate the beads from the solution.




Non-magnetic option



- Centrifuge sample well/tube (1 min, 1300 RPM).
- Remove 350 µL of supernatant and discard.
- Add 150 μL of **SMART Digest IA buffer** (component 3) to your sample up to a final volume of 200 μL.
- Cap wells or tubes.


Magnetic option



- Place magnet to side of well/tube. The beads will be held in place.
- Remove entire 400 µL of supernatent.
- Add 200 μL of the SMART Digest IA buffer (component 3) to your well/tube to give a final volume of 200 μL.
- Cap wells or tubes.

Protein Digestion Procedure

For both non-magnetic and magnetic options.




Digestion Optimization

Optimize the digestion time for your assay

- Prepare eight identical samples using a relatively high, known concentration of native analyte in SMART Digest IA buffer (component 3).
- Digest the samples according to the Protein Digestion Procedure and periodically remove one of the samples from the well or tube (e.g. every 5 to 15 minutes).
- Perform the appropriate Post Digestion Process.
- Analyze the samples to determine the extent of digestion (see diagram and table).

- Identify signature peptides and monitor their MS response. Once the MS response is consistent digestion is complete, the corresponding digestion time can be used for subsequent analyses.
- In the case of IgG the 937 *m/z* ion was monitored and full digestion is shown to be complete in just over 60 minutes.




Typical Digestion Times				
Protein	Digest Time (min)			
Insulin	4			
BSA	< 5			
Carbonic anhydrase	< 5			
Lysozyme	< 5			
Аро-В	30			
IgG	45			
IgG in 50 μL plasma*	75			
Ribonuclease A	150			
Thyroglobulin	240			
C-reactive protein	240			
200 μL protein solution (100 μg/mL) at 70 °C *lgG in plasma (17.5 mg/mL total protein) at 70 °C				

Post Digestion Process



Using SOLAµ SPE Plates


SOLAµ SPE cleanup method



Manifold setup and plate alignment Filtration plate OR



SOLAµ SPE plate




Vacuum manifold top




96-well collection plate in the vacuum manifold base











Points to consider

- No gap between filter/SOLAµ plate and collection plate.
- When under vacuum filter/SOLAµ plate will be held tightly in position.




Practical considerations for the use of filtration and SOLAµ SPE plates

- 1. Using an accurate pipette, aspirate the specified volume of either solvent/reagent, or sample.
- 2. Dispense solvent/ reagent or sample into a unique 'well' of the filtration or SOLAµ SPE plate. Up to 96 wells can be used simultaneously.





- **3.** Apply a gentle vacuum and increase the pressure until the liquid begins to flow through the filtration, or SOLAµ SPE plate.
- **4.** The collected eluent is then kept for analysis.



Characteristics

Product Type	Binding Capacity	
SMART Digest IA kit, Streptavidin	$30~\mu\text{L}$ (1350 $\mu\text{g})$ of beads bind approximately 5 μg biotinylated IgG	
SMART Digest IA kit, Protein A	30 μL (1350 μg) of beads bind approximately 5 μg IgG	
SMART Digest IA kit, Protein G	30 μL (1350 μg) of beads bind approximately 5 μg IgG	
Digestion Time	~ 60 minutes or less (see Digestion Optimization section)	
Concentration	~ 45 mg beads/mL suspension	
Diameter of beads	~ 20 µm	

Operational Specifications

Pre-capture	Post-capture	Capture and Wash	Digestion
Sample Volume	Sample Volume	Temperature (°C)	Temperature (°C)
10–500 μL	≤50 µL	20-25 °C	50-70 °C

Ordering Information

Part Number	Description	
Streptavidin		
60110-101	SMART Digest IA Kit, Streptavidin (Av) non-magnetic	
60110-102	SMART Digest IA Kit, Av non-magnetic with Thermo Scientific™ SOLAµ™ SPE and collection plate	
60110-103	SMART Digest IA Kit, Av magnetic with SOLAµ SPE and collection plate	
60110-104	SMART Digest IA Kit, Av magnetic	
Protein A		
60111-101	SMART Digest IA Kit, Protein A non-magnetic	
60111-102	SMART Digest IA Kit, Protein A non-magnetic with SOLAµ SPE and collection plate	
60111-103	SMART Digest IA Kit, Protein A magnetic with SOLAµ SPE and collection plate	
60111-104	SMART Digest IA Kit, Protein A magnetic	
Protein G		
60112-101	SMART Digest IA Kit, Protein G non-magnetic	
60112-102	SMART Digest IA Kit, Protein G non-magnetic with SOLAµ SPE and collection plate	
60112-103	SMART Digest IA Kit, Protein G magnetic with SOLAµ SPE and collection plate	
60112-104	SMART Digest IA Kit, Protein G magnetic	

Product Storage

- Store SMART Digest IA beads at -20 °C.
- Store Digest buffer and dry or reconstituted SMART Digest IA wash buffer at 4 °C.
- All other materials can be stored at room temperature.

Each SMART Digest IA kit ships in cold conditions. Each kit contains a WarmMark^{®2} Temperature Indicator. This indicator tracks how long the kit has been at, or above, 38 °C by irreversibly turning from white to blue.

If on opening the kit the temperature sensor indicates that the kit has been exposed to 38 °C for more than 2 hours please contact Technical Support: www.thermofisher.com/chromexpert to help determine the functionality of the SMART Digest IA kit.

WarmMark®2 Time/Temperature Indicator



Materials recommended but not provided

- Heater/shaker equipped with heated block and heated lid, capable of uniformly heating samples to 70 °C.
- Thermo Scientific[™] Matrix[™] SepraSeal (P/N 4463) for use with deepwell plates.
- Thermo Scientific[™] DynaMag[™]-96 Side Magnet block, for use with magnetic bead versions of kit (P/N 12331D).
- The Thermo Scientific™ KingFisher™ Duo Prime, or KingFisher Flex Purification Systems (P/N 5400110 and P/N 5400630 respectively) for use with magnetic bead versions of the kit (high throughput options).

For use with SOLAµ SPE plate operation:

- Thermo Scientific[™] HyperSep-96 Well Plate Vacuum Manifold (P/N 60103-351).
- The Thermo Scientific[™] Vacuum Pump NA option (P/N 60104-243) or EU option (P/N 60104-241).
- Thermo Scientific[™] WebSeal[™] 96 Well Collection Plate (P/N 60180-P211).
- WebSeal CLR Silicone 96 Well Mat (P/N 60180-M105).

Recommended column for peptide quantification:

Thermo Scientific™ Acclaim™ VANQUISH™, C18, 2.2 μm Analytical (2.1 × 250 mm, P/N 074812-V).

thermoscientific

Characterize the full diversity of biomolecules

Thermo Scientific™ solutions for biomolecule separations



Find out more at thermofisher.com/SMARTdigest

